

96 x 96mm

SPECIFICATIONS

Description : 1 Ø Digital Ammeter
Display : 4 Digit 7 Segment LED

Display

Rated Input Current : Nominal 5A AC

(Min-50mA, Max-6.2A)

Over Range Indication: "Or" for input > 6.2A

CT Primary

CT Secondary : 1A or 5A

Resolution : Auto Resolution depend

upon CT ratio

: 1-999.0kA

Accuracy : ±0.5% of Full Scale

Measuring Method : True RMS

Display Update Time: 1sec.

Power Consumption: Less than 4VA

Supply Voltage : 40-300V AC/DC, 50/60Hz

Weight : 150gms

Mounting : Panel mounting

Environmental Conditions:

Operating Temperature: -10°C to 55°C

Operating Storage : -20°C to 75°C

Relative Humidity: Upto 85% (non-condensing)

Pollution Degree: II

| | ORDER CODE I | | |
|---|---------------------|------------------------|---------------|
| Γ | Product | Supply Range | Certification |
| | MA32-1-G-40/300V-CE | 40-300V AC/DC, 50/60Hz | V |
| ſ | MA32-1-G-40/300V | 40-300V AC/DC, 50/60Hz | |

SAFETY PRECAUTIONS

All safety related codifications, symbols and instructions that appear in this operating manual or on the equipment must be strictly followed to ensure the safety of the operating personnel as well as the instrument.

If the equipment is not used in a manner specified by the manufacturer it might impair the protection provided by the equipment.

- Do not use the equipment if there is any mechanical damage.
- Ensure that the equipment is supplied with correct voltage.

A CAUTION:

- Read complete instructions prior to installation and operation of the unit.
- 2. Risk of electric shock.
- The equipment in its installed state must not come in close proximity to any heating sources, caustic vapors, oils, steam, or other unwanted process by products.




CONFIGURATION

- Use + key to enter & exit from configuration menu, for 3 sec.
- Use key to go to next parameter.
- Use key to edit the parameter & press same key for 2 sec. to save parameter.
- Use \wedge key to increment parameter value.
- To set the value of CT primary in kA, First edit the value and then press ★ key for 3 sec., Display will shift to kA with resolution 000.0kA & this process is same, to set the value of CT primary in A.

| Config. page. | Function | Range or Selection | Factory Setting |
|------------------|--------------|--------------------|--------------------|
| 2 | CT Primary | 1-999.0kA | 5 |
| 3 | CT Secondary | 1 or 5 | 5 |

SERIAL NUMBER DESCRIPTION

Press key for 10sec. to display 8 digit serial number for 3sec. in two windows



#All fuse types: 0.5A class CC UL type; 0.5A fast acting 600V

(Specifications subject to change as development is a continuous process.)

Selec Controls Pvt. Ltd., India

Factory Address:

EL-27/1, Electronic Zone, TTC Industrial Area, MIDC, Mahape, Navi Mumbai - 400 710. INDIA.

Tel. No.: +91-22-41 418 419/430 | Fax No.: +91-22-28471733 Toll free: 1800 227 353 (BSNL/MTNL Subscribers only)

Website: www.selec.com | Email: sales@selec.com